



Description:

This Dual ESC module is designed for RC micro model tank, crawler and boat DIY.

Size: 19mm*23mm*5mm

Weight: 6g

Input Voltage: 4.2V-9.6V

Current: 6A Maximum

BEC: 5V1A

PWM Frequency: 250Hz

Note:

Option A: Dual Bi-Directional ESC with internal tank mix control function (2 motor mix control, signal 1 control forward/backward, signal 2 control left/right)

Option B: Dual Standalone Bi-Directional ESC (signal 1 control motor B, signal 2 control motor A)

Option C: Dual Bi-Directional ESC with Crawler DIG function (2 motor mix control, signal 1 control 2 motors forward/backward, signal 2 control the DIG function, signal 2 = middle, both motors are running; signal 2 = High, only motor A is running, motor B stop; signal 2 = Low, only motor B is running, motor A stop)

Package Included:

1 x 155A Micro Dual Bi-Directional ESC PCB

2 x Standard JST Servo Cable

1 x Standard Battery Plug Cable Set

4 x Motor Cable

6 x Spark Capacitor (Brushed motor use)